

# Smart Wi-Fi 3-circuit light switch



**Smart control**  
3 independent switches  
for 3 separate lights



**Voice control**  
Requires an Amazon Alexa or  
Google Assistant-enabled device



**Single pole only**  
Not compatible with 3-way  
(multi-location control) circuits



**No hub  
required**



**Easy to  
share access**



**2-year  
warranty**



Your home  
in **one app**

## The easiest way to make your existing lights smart

Nexxt Solutions introduces its new **Smart Home Automation Series**. Designed to suit your mobile lifestyle while building a safe environment inside and out of your home, the brand seamlessly unifies into one user-friendly application a comprehensive line of fully integrated devices. From smart plugs, cameras, bulbs and photo frames to a variety of smart switches, you can now take control and run your home devices, on your own schedule even when you are not there.

Customizing your lights and favorite scenes has never been easier! Designed to upgrade conventional single-pole light controls, our **Smart Wi-Fi 3-circuit switch** can be quickly installed and integrated into your existing wireless network, no hub required. Boasting a modern design along with its fire-retardant construction, this switch emerges as a great addition to any room in the home. Since it's powered by the Nexxt Solutions Home app, users can remotely monitor their lights, fixtures or appliances and set on/off times using a smartphone, at any time and from anywhere. Its voice activation feature makes it compatible with Google Assistant and Amazon Alexa for hands-free management of all linked devices. You can have peace of mind by checking the real-time status of any appliance at any time, save energy by running your house on your schedule, while providing a higher sense of security by making it appear that you are home even though you are halfway around the world.

## Highlights

- Smart 3-circuit light switch – boasting a modern and space-saving design
- Convenient 3-in-1 solution- allows the connection of three separate fixtures
- Each switch can be individually managed and configured
- Designed for energy-efficient LED and conventional bulbs
- Manual and remote on/off controls through the app
- Nexxt Solutions Home App
- iOS and Android™ platform compatible
- No hub required
- Easy pairing
- Voice activated: utter simple commands using your favorite voice assistant
- Create schedules: turn lights and connected loads on or off at specific times, or based on sunrise - sunset cycles
- Push-button with LED to locate the switch in the dark
- Multiple programmable timers
- Share access



Smart HOME. Smart living

# Smart Wi-Fi 3-circuit light switch



## Technical specifications

MPN	NHE-T100
<b>General</b>	
Circuit type	Single pole switch
Nominal voltage	110-240V
Frequency	50Hz/60Hz
Amperage	10A
Rated power	Incandescent: 600W (max) LED: 150W (max)
Wireless frequency	IEEE 802.11N, 2.4GHz (not compatible with 5GHz Wi-Fi networks)
Installation requirements	Neutral wire
Special features	On, Off, Schedule, Timer, Group, Voice Control, Mobile App
Compatible with Alexa	Yes
Compatible with Google Assistant	Yes
iOS/Android compatible app	Yes
Application	Indoor use
<b>Physical appearance</b>	
Dimensions	With panel: 4.6x2.95x1.4in Without panel: 4.5x2.95x1.4in
Housing	Fire-retardant plastic
Color	White
Weight	0.33lb
Type of switch	Toggle button
<b>Environment</b>	
Operating temperature	-4°F to 167°F
Storage temperature	-4°F to 167°F
Relative humidity	<95%
<b>Additional Information</b>	
System requirements	Mobile device running iOS 9 or higher, Android 5.0 or higher Nexxt Home app Existing Wi-Fi network
Package content	- Smart 3-circuit light switch (1) - Mounting screws (2) - Quick setup card (1) - User guide (1 pc)
Certificate	FCC
Warranty	Two years

- This is a single -pole switch, not compatible with 3-way (multi-location control) switch
- Not designed to be used with metal face plates, as it may interfere with the Wi-Fi signal
- Electrical connection with neutral wire required