Smart Wi-Fi relay switch







Voice control Requires an Amazon Alexa or the Google Assistant-enabled device













Modernize your home for a smart life

Nexxt Solutions introduces its new **Smart Home Automation Series**. Designed to suit your mobile lifestyle while building a safe environment inside and out of your home, the brand seamlessly unifies into one user-friendly application a comprehensive line of fully integrated devices. From smart plugs, cameras, bulbs, and photo frames to security kits, you can now take control and run your home devices on your own schedule even when you are not there.

Forget about flipping the switch to turn on or off your home devices with the **Smart relay switch.** Wirelessly control your appliances through the Nexxt Home app to create schedules, set a countdown, share control with users, and lock kids access with this smart relay switch. It helps you oversee your child's routine; turn off the gaming console when it's time to study and turn it on when the homework is complete. You can also create a group of devices to manage their working time and turn them all on or off simultaneously, optimizing time. Save energy by remotely accessing your lamp, fan, sound system, or TV to control them even when you are away. Conveniently manage your home appliances using Amazon Alexa or Google Assistant while cooking, reading, or watching TV. It is a practical solution to automate your home and make it truly smart.

Highlights

- No hub required
- Create scenes with other Nexxt Home products
- Easy pairing
- Nexxt Home app
- Voice activated: utter simple commands using Amazon Alexa and Google Assistant

Ĥ

- iOS and Android[™] compatible app
- Create schedules: turn on or off devices at specific times, or based on sunrise-sunset cycles
- Multiple programmable timers
- Share access
- Maximum power: 2200W







Your home

in one app

NHE-R100

Smart Wi-Fi relay switch



Technical specifications

| MPN | NHE-R100 |
|----------------------------------|--|
| General | |
| Nominal voltage | 110-240V |
| Voltage range | 90-250V |
| Frequency | 50Hz/60Hz |
| Amperage | 10A |
| Maximum power | 2200W |
| Wireless frequency | IEEE 802.11N, 2.4GHz (not compatible with |
| | 5GHz Wi-Fi networks) |
| Additional information | |
| System requirements | Mobile device running iOS 8 or higher, Android |
| | 4.1 or higher |
| | Nexxt Home app |
| | Existing Wi-Fi network |
| Special features | On, off, schedule, timer, group, voice control, mobile app |
| Compatible with Amazon Alexa | Yes |
| Compatible with Google Assistant | Yes |
| iOS/Android compatible app | Yes |
| Application | Indoor |
| Warranty | 2 years |
| Certificate | FCC |
| Physical appearance | |
| Dimensions | 3.7x0.9x1.5in |
| Housing | Fire-retardant plastic |
| Color | White |
| Weight | 0.12lb |
| Type of switch | Relay switch |
| Included in packaging | Smart relay switch (1) |
| | Screw (4) |
| | Wire fastener cover (2) |
| | User manual |
| Environment | |
| Working temperature | 14°F -113°F |
| Storage temperature | 14°F -113°F |
| Relative humidity | <80% |

*Not designed to be used with metal face plates, as it may interfere with the Wi-Fi signal *Does not support CFL bulbs